



DOCUMENTATION

- 1 The Detector is Photoelectric Smoke Detector. It was Designed on theory in which the light emits diffusively to various directions when reflecting onto the smoke cell.
- 2 Soon as the detector sensors the desired density of the Smoke, after several times of confirmation as a flame smok, it then transfers into signal and transmits to signal receiver or control disc to change the fire alarm or activate the equipment of fire resistance gate and smoke expellation value.

FEATURES

- 1 For security system.
- 2 Two-wire low current design 16-32 VDC range
- 3 Base options: for supplementary relay, and / or remote indicator, 2-wire and 4-wire applications.
- 4 Signal source : Highly reliable LED light sources and photodiode sensors: are used.
- 5 The integrated wiring system was designed since 1990

SPECIFICATIONS

| | |
|--------------------------|--|
| Model No | CL-180 |
| Input Voltage | 16V-32VDC (DC 24V) |
| Alarm Current | 10-100mA (MAX) |
| Standby Current | 60 u A average, 90 u A peak @ 24VDC 40 u A average, 60 u A peak @ 16VDC |
| Environmental Temperatur | 32 F - 140F |
| Relative Humidity | 0 - 95% RH |
| Sensitivity | Nominally set at 10% / 50 cm |
| Monitoring Led | BLINKING LED |

DETECTOR STRUCTURE

| Appearance | Weight | Diameter | Height |
|------------|--------|----------|--------|
| Ivory | 170 g | 10.6 cm | 5 cm |

EFFECTIVE WARNING AREA

| Height above the ground | Below 4M | 4-8 M | 8 - 15 M |
|-------------------------|-------------------|------------------|------------------|
| Building | 100M ² | 50M ² | 30M ² |

Detector operating chart

